



Daffodil International University

Faculty of Science & Information Technology

Department of Computer Science & Engineering

Final Semester Examination, Spring 2025

Course Code: CSE335 Course Title: Computer Architecture and Organization

Level: 4 Term: 1 Batch: 61

Time: 2:00 Hrs

Marks: 40

Answer ALL Questions [Optional]

[The figures in the right margin indicate the full marks and corresponding course outcomes. All portions of each question must be answered sequentially.]

1.	a)	<p>A digital control system processes sensor data using a 6-bit binary multiplier. Suppose the system receives two 6-bit binary values, A=101101 and B=011011, which represent sensor readings. The system needs to compute their product to determine the control output.</p> <p>Design a logic diagram to implement this multiplication for A & B.</p> <p>Derive the general equation for multiplying two 6-bit binary numbers and apply it to compute the 12-bit binary product of A and B.</p>	[3+4]	CO2																																																		
	b)	<p>A scientist is using a computer to perform complex mathematical calculations, such as simulating weather patterns. The computer's CPU alone is taking too long to complete the calculations. How coprocessor helps in this situation?</p>	[3]																																																			
2.	a)	<p>From the below figure identify what kind of Hazard it is. Draw the necessary diagrams step by step to eliminate this particular hazard if there is single port available in every clock cycle.</p> <div><p style="text-align: center;">Clock Cycle</p><table><tr><td></td><td>1</td><td>2</td><td>3</td><td>4</td><td>5</td><td>6</td><td>7</td><td>8</td><td>9</td></tr><tr><td>Ins-1</td><td>FI</td><td>DI</td><td>CO</td><td>FO</td><td>EI</td><td>WO</td><td></td><td></td><td></td></tr><tr><td>Ins-2</td><td></td><td>FI</td><td>DI</td><td>CO</td><td>FO</td><td>EI</td><td>WO</td><td></td><td></td></tr><tr><td>Ins-3</td><td></td><td></td><td>FI</td><td>DI</td><td>CO</td><td>FO</td><td>EI</td><td>WO</td><td></td></tr><tr><td>Ins-4</td><td></td><td></td><td></td><td>FI</td><td>DI</td><td>CO</td><td>FO</td><td>EI</td><td>WO</td></tr></table></div> <p style="text-align: center;">Fig 1: Six Stage Pipeline</p>		1	2	3	4	5	6	7	8	9	Ins-1	FI	DI	CO	FO	EI	WO				Ins-2		FI	DI	CO	FO	EI	WO			Ins-3			FI	DI	CO	FO	EI	WO		Ins-4				FI	DI	CO	FO	EI	WO	[1+4]	CO3
	1	2	3	4	5	6	7	8	9																																													
Ins-1	FI	DI	CO	FO	EI	WO																																																
Ins-2		FI	DI	CO	FO	EI	WO																																															
Ins-3			FI	DI	CO	FO	EI	WO																																														
Ins-4				FI	DI	CO	FO	EI	WO																																													
	b)	<p>Suppose you have 12 instructions to process with no-branch. Assume that the instruction cycle time is 8 milliseconds. After identifying the total time required for a pipeline with 7 stages to execute all the instructions, now find out the speedup factor. And sketch the graph accordingly.</p>	[3+2]																																																			

$$\frac{21K}{K+(n-1)} \quad 4.00$$

3.	a)	Assume you have a Main Memory which has a size of 256 Byte and a Cache Memory size of 32 Byte . Each line of cache memory can hold a block of 32 bits words, where each word of size 8 bits . Now, sketch the Cache and Main Memory structure for the above requirements, then show the Associative Mapping from Cache to Main Memory with example of Address Structure using 000000111 address.	[3+4]	CO4
	b)	Analyze which mapping within 3 types, will be effective for the above scenario with the required parameters: Data Loss, Speed, Time .	[3]	
4.	a)	A system administrator at a data center observed unusual memory access patterns processes were accessing segments they typically shouldn't and triggering unexpected page faults, suggesting a potential security breach. Recalling that the Memory Management Unit (MMU) is essential for translating virtual addresses to physical addresses and enforcing memory protection, the administrator initiated an investigation into the MMU's role in system security. Analyze the role of the Memory Management Unit (MMU) in translating virtual addresses to physical addresses to ensure that processes access only their allocated memory. Evaluate the effectiveness of memory access time with a mathematical example if page hit and page fault occurs.	[3+4]	CO4
	b)	Discuss with the help of a diagram that how the demand paging affects overall system performance.	[3]	

0-1 = 1 - 1