



Daffodil International University
Faculty of Science & Information Technology
Midterm Examination, Spring-2023
Course Code: CSE231

Course Title: Microprocessor, Embedded Systems and IoT

Level: 3

Term: I

Batch: 59

Time: 1 Hour and 30 Minutes

Marks: 25

Answer ALL Questions

[The figures in the right margin indicate the full marks and corresponding course outcomes. All portions of each question must be answered sequentially.]

1.	a)	Suppose you have to design a system that has just one task, to turn off a light at a specified time. You will have to use parts that are already available in the market to design this system. Recommend one among microcontroller and microprocessor by comparing the two.	[5]	CO1																
2.	a)	Explain with calculations, for MOV AX, [SI] , from where the value of AX register will come from if DS = 4C60h and SI= last 3 digit of your student ID in hexadecimal.	[5]	CO2																
	b)	MOV DS, AB40h MOV SI, 0B78h MOV AX, 2[SI] ADD AX, 5h For the code above, Determine the final value of AX showing calculations to support your opinion. The address and content of some memory locations are given. <table><tr><th>Address</th><th>Content</th></tr><tr><td>157EF5h</td><td>23h</td></tr><tr><td>157EF4h</td><td>22h</td></tr><tr><td>ABF7Bh</td><td>12h</td></tr><tr><td>ABF7Ah</td><td>A2h</td></tr><tr><td>AB87Ch</td><td>26h</td></tr><tr><td>AB87Bh</td><td>22h</td></tr><tr><td colspan="2">Memory</td></tr></table>	Address		Content	157EF5h	23h	157EF4h	22h	ABF7Bh	12h	ABF7Ah	A2h	AB87Ch	26h	AB87Bh	22h	Memory		[5]
	Address	Content																		
	157EF5h	23h																		
	157EF4h	22h																		
	ABF7Bh	12h																		
ABF7Ah	A2h																			
AB87Ch	26h																			
AB87Bh	22h																			
Memory																				
		For each of the cases below, determine the value of SF, ZF, PF, CF and OF and justify the values with proper reason.																		
c)	SUB AL, BL Given, AL= 0Fh and BL= 1Fh	[2.5]																		
d)	NEG AX Given AX=0000h	[2.5]																		
3		Apply the idea of loop to write an assembly code to output the odd numbers between 0 and 10.	[5]	CO3																